

## Technical Note - SolarEdge Home Network Plug-in Kit Selection

Refer to the table below to select the appropriate SolarEdge Home Network Plug-in kit for your inverter.

For installation instructions, refer to the installation guide that comes with the kit.

Inverter	Inverter Part Number	Inverter Cellular Socket Occupied?	SolarEdge Home Network Plug-In Kit Part Number
<b>SolarEdge Home Wave Inverter with SetApp</b> (SolarEdge Home Network ready)	SExxxxH-RWxxxBE <sup>xx</sup>	Not applicable	<b>ENET-HBNP-01</b> SolarEdge Home Network Plug-in
<b>SolarEdge Home Wave Inverter with SetApp</b> ( <i>Not</i> SolarEdge Home Network ready)	SExxxxH-RW0 <sup>xx</sup> BN <sup>xx</sup>	No	<b>ENET-HBCL-01</b> SolarEdge Home Network Plug-in
		Yes	<b>ENET-HBPV3-01</b> Kit containing SolarEdge Home Network-ready comm. board* and matching SolarEdge Home Network Plug-in
<b>StorEdge Single Phase Inverter</b> ( <i>Not</i> SolarEdge Home Network ready)	SExxxxH-RW <sup>Sxx</sup> BN <sup>xx</sup>	No	<b>ENET-HBCL-01</b> SolarEdge Home Network Plug-in
		Yes	<b>ENET-HBPV3S-01</b> Kit containing SolarEdge Home Network-ready comm. board* and matching SolarEdge Home Network Plug-in
<b>SolarEdge Home Wave Inverter with LCD</b> ( <i>Not</i> SolarEdge Home Network ready)	SExxxxH-RWxxxN <sup>xxx</sup>	Not applicable	<b>ENET-HBPV3D-01</b> Kit containing SolarEdge Home Network-ready comm. board* with LCD and matching SolarEdge Home Network Plug-in
<b>Single Phase Inverter with Compact Technology</b> ( <i>Not</i> SolarEdge Home Network ready)	SExx00M-RWK02BNN4	No	<b>ENET-HBCL-01</b> SolarEdge Home Network Plug-in
		Yes	<b>ENET-HBPVL-01</b> Kit containing SolarEdge Home Network-ready comm. board* and matching SolarEdge Home Network Plug-in
<b>Three Phase Inverter with SetApp</b> (SolarEdge Home Network ready)	SExxK-RW0 <sup>xx</sup> BE <sup>xx</sup>	Not applicable	<b>ENET-HBNP-01</b> SolarEdge Home Network Plug-in
<b>StorEdge Three Phase Inverter</b> (SolarEdge Home Network ready)	SExxK-RWS <sup>xx</sup> BE <sup>xx</sup>	Not applicable	<b>ENET-HBNP-01</b> SolarEdge Home Network Plug-in
<b>Three Phase Inverter with SetApp</b> ( <i>Not</i> SolarEdge Home Network ready)	SExxK-RW0 <sup>xx</sup> BN <sup>xx</sup>	No	<b>ENET-HBCL-01</b> SolarEdge Home Network Plug-in
<b>StorEdge Three Phase Inverter</b> ( <i>Not</i> SolarEdge Home Network ready)	SExxK-RWS <sup>xx</sup> BN <sup>xx</sup>	Yes	<b>ENET-HBPJ25-01</b> Kit containing SolarEdge Home Network-ready comm. board* and matching SolarEdge Home Network Plug-in

<b>Three Phase Inverter with LCD</b> ( <i>Not</i> SolarEdge Home Network ready)	SExxK-RWxxxNxxx	Not applicable	<b>ENET-HBPJD-01</b> Kit containing SolarEdge Home Network-ready comm. board* with LCD and matching SolarEdge Home Network Plug-in
<b>Three Phase Backup Inverter</b> (SolarEdge Home Network ready)	SExxK-RWB48xxxx	Not applicable	<b>The SolarEdge Home Network Plug-in and Antenna are provided with the inverter. No additional kit is required.</b>

\* Replace the existing communication board with a communication board that has a dedicated socket for the SolarEdge Home Network Plug-in.